

## Lighting Tables for Existing/Base Equipment

4/13/2015

### T12 Fluorescent Lamps and Fixtures

LAMP LENGTH	DESCRIPTION	NUMBER OF LAMPS	CODE	WATTS	LAMP LENGTH	DESCRIPTION	NUMBER OF LAMPS	CODE	WATTS
2'	F20T12	1	8000	28	5'	F60T12	1	8029	100
		2	8001	46			2	8030	135
		3	8002	68		F60T12 HO	1	8031	126
		4	8003	91			2	8032	170
3'	F30T12 (30 watt lamps)	1	8004	43			3	8033	250
		2	8005	70			4	8034	330
		3	8006	113		F60T12 VHO	1	8035	157
		4	8007	138			2	8036	310
3'	F30T12 (25 watt lamps)	1	8008	40	6'	F72T12	1	8037	107
		2	8009	63		2	8038	145	
		3	8010	103		F72T12 HO	1	8039	135
		4	8011	125			2	8040	195
4'	F40T12 (40 watt lamps)	1	8012	46			3	8041	265
		2	8013	81			4	8042	330
		3	8014	123		F72T12 VHO	1	8043	180
		4	8015	161			2	8044	300
4'	F40T12 (34 watt lamps)	1	8016	43	3		8045	450	
		2	8017	72	8'	F96T12 (75 watt lamps)	1	8046	100
		3	8018	115		2	8047	180	
		4	8019	144		F96T12 (60 watt lamps)	1	8048	75
F48T12	1	8020	55	2			8049	123	
	2	8021	93	F96T12 HO (110 watt lamps)		1	8050	139	
F48T12 HO	1	8022	76			2	8051	257	
	2	8023	130			3	8052	330	
	3	8024	195	F96T12 HO (95 watt lamps)		1	8053	125	
	4	8025	260		2	8054	227		
F48T12 VHO	1	8026	134	F96T12 VHO (215 watt lamps)	1	8055	230		
	2	8027	240		2	8056	375		
	3	8028	450		3	8057	570		
					F96T12 VHO (185 watt lamps)	1	8058	200	
						2	8059	325	

### Existing/Base Incandescent or Halogen Lamps

LAMP WATTAGE	WATTS	CODE	LAMP WATTAGE	WATTS	CODE
6 Watt	6	8095	200 Watt	200	8065
40 Watt	40	8060	300 Watt	300	8066
50 Watt	50	8097	450 Watt	450	8096
60 Watt	60	8061	500 Watt	500	8067
65 Watt	65	8102	575 Watt	575	8098
75 Watt	75	8062	750 Watt	750	8068
90 Watt	90	8107	1000 Watt	1000	8069
100 Watt	100	8063	1500 Watt	1500	8070
150 Watt	150	8064			

## Lighting Tables for Existing/Base Equipment

4/13/2015

### Existing/Base T8 Lamps

DESCRIPTION	WATTS	CODE
4' - 32 Watt T8 Lamps Only (Use Codes 475 through 478 for New Equipment Code)	32	8091

### Existing/Base T5 Lamps

DESCRIPTION	WATTS	CODE
54 Watt T5 HO Lamps Only (Use Codes 2088 and 2089 for New Equipment Code)	54	8101

### Existing/Base Mercury Vapor Fixtures

DESCRIPTION	WATTS	CODE	DESCRIPTION	WATTS	CODE
50 Watt - 1 lamp	118	8071	400 Watt - 2 lamp	880	8075
100 Watt - 1 lamp	125	8072	500 Watt - 1 lamp	570	8077
175 Watt - 1 lamp	205	8073	700 Watt - 1 lamp	775	8078
250 Watt - 1 lamp	285	8074	1000 Watt - 1 lamp	1080	8079
400 Watt - 1 lamp	454	8076			

### Existing/Base Metal Halide Lamps

DESCRIPTION	WATTS	CODE
250 Watt Metal Halide Lamps Only (Use Code 983 or Code 984 for New Equipment Code)	250	8099
400 Watt Metal Halide Lamps Only (Use Code 985 or Code 986 for New Equipment Code)	400	8100
1000 Watt Metal Halide Lamps Only (Use Code 991 or Code 992 for New Equipment Code)	1000	8103

### Existing/Base Metal Halide Fixtures

DESCRIPTION	WATTS	CODE	DESCRIPTION	WATTS	CODE
32 Watt - 1 lamp	41	901	400 Watt - 1 lamp	458	8089
50 Watt - 1 lamp	67	905	400 Watt - 2 lamp	916	8090
70 Watt - 1 lamp	92	909	750 Watt - 1 lamp	850	8104
100 Watt - 1 lamp	129	913	1000 Watt - 1 lamp	1080	8092
150 Watt - 1 lamp	190	8086	1000 Watt - 2 lamp	2160	8093
175 Watt - 1 lamp	215	8087	1000 Watt - 3 lamp	3240	8094
250 Watt - 1 lamp	295	8088			

### Existing/Base High Pressure Sodium (HPS) Fixtures

DESCRIPTION	WATTS	CODE	DESCRIPTION	WATTS	CODE
35 Watt	41	903	70 Watt	92	911
50 Watt	67	907	100 Watt	129	915

### Existing/Base Exit Signs

DESCRIPTION	WATTS	CODE	DESCRIPTION	WATTS	CODE
15 Watt - 2 lamp Incandescent	30	8080	20 Watt - 2 lamp Incandescent	40	8081

**Definitions:**

HO - High Output

VHO - Very High Output